🔊 sensolus

The rugged low-power tracker with long battery life with NB-IoT connectivity and guaranteed data recovery. The tracker provides general localization, zone and high precision. Compatible with multiple external environmental sensors. The tracker firmware can be upgraded over the air.

- 🕷 GNSS
- Wi-Fi scanning
- ✤ Bluetooth geobeacon for zone precision
- Quuppa tested for high precision
- NB-IoT
- S Europe and North America
- Data recovery
- Up to 10 years of battery life
- ♦ IP68 & IP69K
- **†** IK10
- Flame retardant

Connectivity

NB-IoT

- Energy efficient transceiver
- · Internal omnidirectional antenna
- · Bi-directional communication
- NB-IoT bands: Europe and North America
- Data recovery
- OTA firmware upgrade (NB-IoT)

Geolocalization

GNSS

- · REV 1: GPS only receiver
- REV 2: Multi GNSS constellation chipset (GPS+GALILEO)
- Patch antenna for optimum performance

BLE


- Sensolus proximity beacon detection
- · Detectable by zone and high precision anchors


Bluetooth Low Energy (BLE)

- BLE 2.4 GHz
- Bluetooth Low Energy 5.0

Wi-Fi scanning

Wi-Fi based geolocalization





Sensing

Internal

- · Activity monitoring
- Orientation monitoring
- Virtual tamper detection

Mounting

- Holes 7x9mm ($^{9}/_{32} * {}^{23}/_{64}$ in) for screws or rivets. 115 mm ($4^{17}/_{32}$ in) distance between the centers of the mounting holes.

Mechanics & design

Antennas All antennas are internal

Size $130x72x36 \text{ mm} (5^{1}/_{8} \times 2^{53}/_{64} \times 1^{27}/_{64} \text{ in })(L \text{ W H})$

Weight 200 gram (7 oz)

Color Translucent black

Casing

Polycarbonate (lexan 943A)

- Flame retardant
- UV-stabilized

Battery

Standard 3 cell

- $\cdot~$ Up to 10 years battery life depending on operating mode
- User replaceable battery pack (Li-SoCl₂) 10500 mAh
- 2.8 gram (0.0987oz) lithium

Certifications

Regulatory

- · CE
- FCC ID 2AQYP-TRACK1100
- FCC ID 2AQYP-TRACK1100R2

Electrical safety

EN-60905-1

Environmental BLE sensors

- Temperature, humidity, air quality
- Person presence, contact, magnet
- Other BLE sensors can be added
- Cable ties
- Double sided tape
- Magnets

Water & dust resistance IP68 & IP69K with automotive-grade venting membrane

Impact resistance IK08 & IK10 (frontal impact)

Drop shock and vibration EN 60068

Operating temperature -20 to 60°C, optional to 80°C (-4°F to 140°F, optional to 176°F)

Storage temperature

-40 to 85°C (-40°F to 185°F)

Bluetooth 5.0 Declaration ID: D048003

Device activation

Magnetic activation

Synchronize remote settings

- Instant: Magnet activation
- Periodic: No user interaction needed

Management services

Diagnostics

- Battery lifetime prediction
- · Detailed energy consumption
- · Geolocation diagnostics
- Installation
- Communication quality

Application services

- Localization
 Activity
- · Journeys · Utilization

Firmware configuration

Communication service

- Data recovery strategy
- Communication conditions

General configuration

- Rule engine configuration
- Diagnostic levels
- Boot methods
- \cdot Accurate time synchronization

Orientation service

Orientation detection parameters

Activity service

Activity detection parameters

LED feedback

Green & red LED feedback on the device

Management

- · OTA firmware updates over NB-IoT and BLE
- Remote configuration
- Tracker usage profiles
- External environmental sensors
- Connectable with
 Tilt detection
 environmental sensors

Location service

- · Motion based, context based, periodic or scheduled
- Configurable update rate and journey detection
- Priority sequence (GNSS, Wi-Fi scanning , Bluetooth geobeacon)
- GNSS fix parameters
- · Quuppa tested for high precision
- Indoor detection algo
- Wi-Fi scan strategy
- BLE scan strategy

Environmental sensing

- Polling and aggregation strategy
- Alerts
- · Edge processing parameters

Tamper service

Virtual tamper algo configuration

Security

- \cdot $\,$ Device unique encryption keys
- $\cdot~$ End to end payload encryption Chacha 20
- $\cdot~$ AES encrypted firmware
- $\cdot\;$ Firmware upgrade allows only signed firmware images